

#### TECHNICAL OVERVIEW

# **S8780A Wireless Device Solution**

Verify Your Wi-Fi 6E and 802.11be Designs

### Look to the Future with a New Solution for IEEE 802.11 Testing

While fifth generation (5G) gets a lot of attention, the Institute of Electrical and Electronics Engineers (IEEE) 802.11 is not standing still. Higher data rates are available today with 802.11ax. Further improvements in speed with higher-order modulation and larger signal bandwidth are planned. The next wireless local area network (WLAN) standard, 802.11be, will support higher bandwidth and modulation than 5G does today.



Figure 1. Evolution of WLAN technologies

Signal bandwidths up to 320 MHz – twice the bandwidth of 802.11ax signals today – and 4096 quadrature amplitude modulation (QAM) are two of the biggest changes introduced within the physical layer (PHY) of this new technology.

The S8780A is ready. Verifying Wi-Fi 6E and 802.11be devices is quick and easy with bandwidth to 800 MHz and frequency to 7.3 GHz. Generating and analyzing 1024QAM and 4096QAM signals uses application software based on Keysight's familiar PathWave Signal Generation and X-Series Applications.



The 3rd Generation Partnership Project (3GPP) is investigating the extension of Long-Term Evolution (LTE) and 5G into unlicensed spectrum above 6 GHz as part of Release 17, planned for December 2021. The S8780A is ready today with applications to test LTE and 5G.

#### Maximize Throughput without Sacrificing Flexibility

More bands and more antennas would seem to add test time and reduce throughput. The 32 ports of the S8780A flexibly test multiple bands, multiple antennas, and multiple devices supporting many use cases.

#### Simplify your test system

The S8780A solution makes it easy to test the three WLAN bands. Each of the 32 ports supports all three bands and is configurable as half duplex or full duplex. Disconnecting and reconnecting your device to test in a different band is unnecessary saving valuable test time.

Internal switching and splitting of signals eliminate the need for separate test system components reducing calibration time and test system maintenance. Configure each port to calibrate and verify every antenna, no matter the frequency or bandwidth. Testing multiple devices and/or multiple antennas is your choice.





Figure 2. Test four mobile phones or one Access Point (AP) with eight antennas

Making startup quick and painless, a controller is embedded within the S8780A solution. Software licenses and applications are loaded before shipment - just plug it in, switch it on, and you are ready to test.

#### Verify multiple wireless technologies

The evolution of 5G and WLAN creates a market for devices using both technologies. Consumer Premises Equipment (CPE) and mobile phones are two examples. Verifying 5G and WLAN in one test plan is easy using the S8780A.

Bluetooth® and IEEE 802.15.4, used for short-range communications, are commonly combined with WLAN in devices. Adding these technologies to a WLAN test plan is simple with the S8780A.

## A Full-Featured Solution for Design Verification Test (DVT)

Essential to every WLAN test solution are chipset control, automation, and test sequencing. In addition to these, the S8780A supports:

- IEEE 802.11a/b/g/j/p/n/ac/af/ah/ax
- Modulation up to 4096QAM
- Multi-User Multiple Input Multiple Output (MU-MIMO) and Orthogonal Frequency-Division Multiple Access (OFDMA) with statistics and RF performance for each user

2	: 🜒 🎑 🞑 💽	tart 🔳 Stop 💾 Save Re	sults 💽 Pr	reset 对	SigMoni	itor Auto-	Range ┥	Sync Inst S	ettings 📲	Sync Inst Re	sults	>    Measure	ement Stopp	ed		👗 Sav	ve Inst State 🗾	Load Inst State	ТАР				Full Screen
VS	G Action : 🚺 Star	Play 🛞 Stop Play 🔇 Ti	rigger Init 📔	💾 Save to	Header	Source P	laying			ARB Gene	ration :	) Generate	e 🕕 Paus										
א ה	G Settings	ů x	2:[EV]	4 User Info	Summai	rv] 6 : [E	VM Error Su	mmary] 1	.0 : [EVM EV	M vs. Symbol	1 14	: [MIMO Burst	Sig Info]	18 : [MIMO Con	nstellation 31 22	2 : [MIMO Constell:	tion 7] ▼ ×	8 : [EVM Bu	rst Sig Info]				• ×
2	1. VISA Information		( united									-						0. DAL 0	Cin Info				
5	VISA Address	TCPIP0::127.0.0.1::hislip0	oser mio	innation 3	unnary.													o . Evm buist	sig into				
2	Connect Enable	True																OFDM Data 8	Burst Info;				
2 4	2. Source Configurations	10.00 10	liser	RU	RU	SubCarrier	MCS	Mod	Power/dBr	<ul> <li>EVM(dB)</li> </ul>	D/F	Data	PSDU	IO Gain	Quadrature	Time Skew	· ·						
2	Amplitude	-10.00 dBm		Index	Size	Indices		Format	Power(up)	inf CVM(00)		rate(Mbps)	CRC	Imbalance	(dB) Error(deg)	Error(ps)		Burst Info Tvi	e: Mod Format	Len(sym)	Par(dBm)	EVM(dB)	
1	Manadam Dath	2412 000 000 GH2																					
	Waveform Name	11 av90M mfm	User1		106	-4991-394	8	2580 AM	-22.43	-41.57	P	9.00	-					L-STF	BPSK		-13.71		
	Sample Bate	100 0000000 MHz	User2		106	-365 : -260		256Q.AM	-21.90	-42.09		38.20						L-SIG	BPSK		-13.41	-36.06	
	Modulation On	Tone	User3		106	-257 : -152	8	256Q.AM	-21.77	-42.38	P	38.20						R-LSIG	BPSK		-13.40	-35.82	
	Play Mode	Continuous	User5	6	106	-123 : -18	ŝ	256QAM	-21.93	-42.18		38.20						HE-SIGA1	BPSK		-13.37	-44.37	
	Output Port	RF10 2	User6					256QAM	-22.49			38.20						HE-SIGB	QPSK	4	-13.46	-41.51	
	3. Source MIMO Settings		User7	9	26	125 : 160		258QAM	-28.85	-41.67	8	9.00						HE-STF	BPSK		-13.10		
	Sync Config	None	User9		106	260 : 365	8	256QAM	-24.64	-40.34		38.20						HE-LTF	BPSK		-13.36		
			User10			367:392		256Q.AM	-31.69	-40.13		9.00						Total			-13.42	-40.63	
			User11	13	105	394 : 499		256QAM	-26.56	-38.90	P	38.20											
																		Radio Std:	11ax 80MHz				E
			HE-SIG-E	3 User Fiel	d:																		
																		MU SIG-A Fi	elds				
			User	STA-ID	NSTS	Beamformin	ng MCS	DCM	Coding								8						
0	utput Port		LinerO	335					1080									UL/DL: DL	SIGB MCS:	1 SIGB DCM:		BSS Color: 5	Bandwidth:
D	rects the Signal Generator to the s	elected port.	User1	388					LDPC									Contial Reur	at 1 Num of SIGB	Symbols Or M	IL MINO LIF ARE		SIGRCompr
N	ore: the port cannot aready be con	rigured for input, if all availa	User2	482					LDPC														
T	VSG Settings 📧 Waveform (	enerator Settings	User4	747		0	8		LDPC									GI+LTF Size:	3 Doppler: 0	TXOP Dural	ion: 8 us	Number of HE	LTF Symbols:
V	A Settings	Д×	User6 User6	760 904		0	8	0	LDPC									LDPC Extral	Symbol: 1	STBC: N	Pre-FEC Pad	ding Factor: 3	
	Holdoff On	D#	User7						LDPC									PEDisambig	uity: 0	CRC: 0x7	Tail: 0x0		
	Holdoff Time	2 000 000 0 us	Usera	1051		0	8	Š.	LDPC									-					
	Holdoff Type	Below	User10	1511		ŏ			LDPC														
	5. Mode Settings	Polon	User11	1319					LDPC									OFDM L-Sig	Info				
	Wan Radio Format	802.11ax 80MHz																					
	Auto Detect Radio Std	0#	HE-SIG-E	Common	Block Fie	ld:												Date: CMDite	Received: 0	1 401 226	Parity: 0	Tail: 0x0	
	6. Measurement State																	Trace, ormering	a meanveu.o	2011.200	Parity. 0	run, oxo	-
	CHP On	False =				Center												<	_	m		_	•
	SEM On	False	RU#(24	(2) RUAllo	cation	26-tone RU	CRC	Tailing										3 : TEVM Fr	or Summary1	27 : IMIMO S	EM 41 31-6	VEMO SEM 81	₹ ×
	EVM On	True																					
	MIMO On	False	RU1	100000		0	0111	000000										RMS EVM					^
	MIMO Combined SEM On	False	RU3	100000		õ	0111	000000										Max	Avg				
	PVT On	False	RU4	100000	00	0	0111	000000									*	-41,186	dB -41.1	86 dB			*
	One Burst Measurement(PVTEV	M) ( False	7 · IEVM	Constell	tion	= x	/ 11 · /FV	U FUM or Su	hcarrier				- X	9 · IEM E	Mus Samboll		- X	Peak EVM:					
	CCDF On	False		Constella		· ^	/	n e m V3: 30	ocomet)					J. LOWIE	ann an agrindoit		• ^	Max	Avg				
	Spectral Flatness On	False			Manager 1	<b>T</b>		11 : EVM EVI	Vs. Subcar	rrier		Zoom	ted:False	9	EVM EVM vs. Sym	lod	Zoomed:False	-29.318	dB -29.3	18 dB			
1	7. Meas Settings		886	100		17,016	-33.000	STREET LAND	Laundan	- land		المواللية سيمتطيه	- Administra	20.000		Terrare Terrar		Pilot EVM:					
	Average State On	False	202	20 al -	10.00	points	dB	Sinding and				Links hitse	*	dB III	0.000 as		*	Max	Avg				
	Average Lount	10	100	60 M.)	VA ANZ		Loo	-60.000 66						Log	0.000/08			-40,471	dB -40.4	71 dB			
1	a. Advanced Settings	•	10 233	cos	1000		Magnitude	RUI .		-US		RUID		Magnitude	0.000 d5			Data EVM					
B	ange		- B.D.	1000			-100.00			RUS	PUR	RU11	9 112	-80.000	0.000 dB			Max	Avg				
S	ets the input range (in dBm).				dealer.	¥.	dB		RU4			U9	RUID	dB 🖓	0.000/dB			-41.221	dB -41.2	21 dB			
			888	1000	1000			Dank EDD C				Phone 500	C		Hank O anna haila		and the sumbals	Frequency E	rror(Hz):				
			688	7122	1.646			Divitic-500. Ci	1000			3t0p:500	- All the loss		sumo. Symbols	51	op-no-symools	Max	Avg				
	VSA Settings 📧 Display Sett	ngs																-2.3742	Hz -2.37	42 Hz			-
Ĩ	Errors Warnings and Inform	tion																					

Figure 3. 802.11ax MU signal generation and analysis

- Arbitrary waveform generation for Single-User (SU) Physical Layer Convergence Protocol (PLCP) Protocol Data Units (PPDU) and MU PPDU with different Resource Unit (RU) sizes, power levels, etc.
- Up to 4x4 true MIMO and 4x4 switched MIMO
- Simultaneous testing of dual-band and triple-band devices
- Channel power, transmit spectral mask, spectral flatness, and Error Vector Magnitude (EVM) measurements



Figure 4. Transmit spectral mask results

torn OFDM		Mode	N 2 Aution Analysis	WLAN Modu	43 lation Anal	ysis	·	+								0		
EYSIGHT	Input RFI02 Output HFI0 Coupling AC		Input 7: 50 D Corrections: Cell Prog Rot Extornal						r Froq unit >1 Info (fi	6 7000 510 20 11=						Rado Sh Adi Mar	1Dolection	5:00
Polar Netrics	•				2 IIQ Mea	and Four 🔹										Radio St	1	Radi
																Rado Se	tings	Im
																Modulatio Auto Del	n Format act 🔹	Syn
																Subcerte	r Sancina	Den
		Max	-44 90 dtl													\$24.0		
	OILS EVEL	Avg	-45.53 dB													312 500	00 1010	10
F	INS EVM	Max	-\$1.85.00													HE SIDE	1117	
		1000	44,13,481													Specing		80
	like EVM	Awa	44 10 (11													70.1250	0.1414	~
		Max	-64 90 dH															1.00
	INA PVM	Avg	H5-19 d0													HE Guan	1 Interval	1.00
E C		Max	1.197.162													Connection		
		Ang	(074-4miHz													A620139		~~
2	iventical	Max	0.06 ppm													HEITER	OF-	
5	look Error	Ang	0.01ppm													Auto Det	et e	
	o congen	ALC: N	100 013 000													<b>Manufacture</b>		
2	and Danst	Marr	-0.07 1995															
1	2005	Aun	-0 t0 #8m															
	ing Barst	Max	11.05 (0)															
		Avg	-11 06 dile															
	me citiset		20156-045															
	and Date	Max	0.09%															
0		A09																
6	Net Error	Aug	o uo peg															



## IEEE 802.11ax Measurement Summary

#### Transmit specification

WLAN application software analyzes WLAN signals captured by the Vector Signal Analyzer (VSA).

IEEE 802.11ax (D6.1)	Description	WLAN application software
27.3.19.1	Transmit spectral mask	Spectrum emission mask
27.3.19.2	Spectral flatness	Spectral flatness
27.3.19.3	Transmit center frequency and symbol clock frequency tolerance	Frequency error and symbol (chip) clock error
27.3.19.4.2	Transmit center frequency leakage	IQ origin offset
27.3.19.4.3	Transmitter constellation error	RMS EVM
27.3.19.4.4	Transmitter modulation accuracy (EVM) test	Modulation analysis

#### **Receiver specification**

WLAN application software generates baseband waveforms, downloads them into the Vector Signal Generator (VSG) memory, then modulates and transmits WLAN signals at Radio Frequencies (RF) with power levels as required for WLAN receiver testing.

IEEE 802.11ax (D6.1)	Description	WLAN application software
27.3.20.2	Receiver minimum input sensitivity	Waveforms for defined PPDU
27.3.20.3	Adjacent channel rejection	Waveforms for wanted and adjacent signals
27.3.20.4	Nonadjacent channel rejection	Waveforms for wanted and non-adjacent signals
27.3.20.5	Receiver maximum input level	Waveforms for defined PPDU

## The S8780A Is the Solution to Verify Your WLAN Designs

Speed your test development, design verification, and manufacturing test with just the right capability and flexibility.

- Be ready for the future with bandwidth to 800 MHz and frequency to 7.3 GHz.
- Get the flexibility you need to optimize your test cases with up to 32 ports.
- Simplify your test system configuration with internal switching between ports.
- Analyze performance using industry-proven application software.

## S8780A Wireless Device Solution: Easy to Use, Flexible, and Future-Proof

A solution for your lab, your bench, and your production line, the S8780A is ready to test your WLAN designs. Right out of the box, its familiar application software is licensed to your specifications. Software-only upgrades and three bandwidth options ensure you get just what you need today and tomorrow.

Visit www.keysight.com/find/e6680a, or contact your sales representative for details.

*Bluetooth*<sup>®</sup> and the *Bluetooth*<sup>®</sup> logos are registered trademarks owned by Bluetooth SIG, Inc., and any use of such marks by Keysight Technologies is under license.

# Learn more at: www.keysight.com

For more information on Keysight Technologies' products, applications or services, please contact your local Keysight office. The complete list is available at: www.keysight.com/find/contactus

